iJRASET

International Journal For Research in
Applied Science and Engineering Technology

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 6 Issue: VI Month of publication: June 2018

DOI: <http://doi.org/10.22214/ijraset.2018.6303>

www.ijraset.com

Call: 08813907089

E-mail ID: ijraset@gmail.com

Speed Control of Wind Powered Sensorless BLDCM Implementing Zeta Converter with PFC

Tito Joseph Francis¹, Ginnes K John²

^{1,2}Dept. of Electrical and Electronics Engineering, Rajagiri School of Engineering & Technology, Kakkanad, Kerala, India

Abstract: This paper propose a simple and cost-effective method of speed control and PFC (Power Factor Correction) of a wind powered BLDCM (Brushless DC Motor). A wind powered single phase supply followed by a universal bridge rectifier, filter and a Zeta DC-DC converter is used to control the voltage of a DC link capacitor connected to a VSI (Voltage Source Inverter) and BLDCM. The proposed control algorithm eliminates speed sensors and uses differential back EMF (Electromotive Force) for switching of VSI, thus making the drive sensorless. ZETA converter is designed for PFC and DC link voltage control to achieve the speed control of Sensorless BLDCM. The proposed drive is designed and its performance is evaluated using MATLAB Simulink and validated using hardware implementation.

Keywords: Brushless DC Motor (BLDCM), Power Factor Correction (PFC), Permanent Magnet (PM), ZETA Converter, Voltage Source Inverter (VSI), Electromotive Force (EMF)

I. INTRODUCTION

In the past decades, we have seen a spurring growth in technology, increased awareness about depletion of fossil fuels and a boom in extracting green energy sources cost effectively and efficiently. A lot of standalone applications such as irrigation and lighting using renewable energy especially solar and wind are getting wide traction nowadays. Several research has been done with solar photovoltaic (SPV) and wind power in combination with various dc-dc converters and motor drives, the zeta converter with PFC in association with BLDCM is not explored to develop such kind of system. Such a combination will contribute to standalone application with improved power quality and to develop a wind powered system that can operate efficiently under dynamically changing atmospheric conditions.

The Brushless DC motor is the ideal choice for the applications that require high reliability, high efficiency and low maintenance [12]. Being a brushless motor, BLDC motor are high performance low maintenance motor capable of providing large amounts of torque and speed performance characteristics. Conventionally a single phase BLDC motor is fed from an AC main through a diode bridge rectifier (DBR) followed by a DC capacitor and a VSI as shown in Fig. 1. Due to uncontrolled charging of the DC capacitor, pulsed AC currents are produced which affect the power factor and in turn result in power quality disturbances. In order to drive the BLDC motor with power quality improvement it needs PFC converter topology among various available topologies [9].

The basic DC-DC converters such as buck, boost and buck-boost have their intrinsic limitations when used for both active PFC and voltage regulation.

Among the new classes of DC-DC converters CUK, SEPIC and Zeta, in the proposed model a Zeta converter is used for active PFC and voltage regulation, having advantages of being naturally isolated structure, it can operate as both step up and step down voltage converter and having only one stage processing for both voltage regulation and PFC [6]. It also facilitates the soft starting of BLDC motor unlike a boost converter which habitually steps up the voltage level at its output, not ensuring soft starting [1].

Unlike a classical buck-boost converter [3], the zeta converter has a continuous and ripple free output current. Although consisting of the same number of components as a Cuk converter [2],

The zeta converter operates as non-inverting buck-boost converter unlike an inverting buck-boost and Cuk converter.

This property obviates a requirement of associated circuits for negative voltage sensing, and hence reduces the complexity and probability of slow down the system response [4].

Fig. 1 Conventional wind-fed BLDC motor drive

II. CONFIGURATION OF PROPOSED SYSTEM

The structure of the proposed wind powered BLDC motor drive employing zeta converter is shown in Fig. 2. The proposed system consists of (left to right) an AC source from the wind turbine, a diode bridge rectifier (DBR), filter, zeta converter, a VSI and a BLDC motor. A pulse generator provides gate signal to the switch S_z of zeta converter. Electronic commutation drives the VSI switches.

Fig. 2 Proposed BLDC motor drive system

III. OPERATION OF PROPOSED SYSTEM

The wind turbine generates the electrical power demand of the BLDC motor. The electrical power is delivered to BLDC motor from the source after two conversions through a DBR, zeta converter and VSI as shown in Fig. 2. The zeta converter works under Continuous Conduction Mode (CCM). Initially when the zeta converter switch S_z is turned ON the diode D_1 is reverse biased, the inductors L_1 and L_2 starts charging and capacitor C_1 starts discharging. When S_z is turned OFF the diode D_1 starts conducting, the inductors L_1 and L_2 starts discharging through the closed circuit formed by the diode and capacitor C_1 starts charging. The zeta switch S_z is switched ON ensuring CCM is achieved. The zeta switch S_z is controlled by a pulse generator which compares

reference voltage and voltage feedback from the output of the zeta converter and produces necessary switching pulses. By changing the reference voltage, the speed of the motor is varied.

The VSI converts the dc output of the zeta converter into ac supply to drive the BLDC motor. The VSI is operated through a electronic commutation assisted by back EMF. Since the positions sensors are avoided and back EMF is used the switching losses are eliminated and the motor is driven efficiently.

IV. DESIGN OF PROPOSED SYSTEM

The proposed zeta converter is designed for BLDC motor with main consideration on PFC. The zeta converter is designed for the parameters shown in Table 1. Due to change in wind speeds the input AC voltage can vary from 10V to 14V. The instantaneous value of duty ratio is expressed as

$$D = \frac{V_{dc}}{V_{dc} + V_{ac}}$$

The minimum value of input inductor L1 for CCM is expressed as

$$L1 = \frac{V_{dc}DT}{\Delta I_{ac}} = \frac{10 \cdot 0.629 \cdot 50 \cdot 10^{-6}}{0.5 \cdot 5} = 125.8 \text{mH}$$

TABLE I DESIGN PARAMETERS

Input AC Voltage V_{ac}	12V
Output DC Voltage V_{dc}	24V
Output Power P	50W
Switching Frequency f_s	20KHz

The minimum value of output inductor L2 for CCM is expressed as

$$L2 = \frac{V_{ac}DT}{\Delta I_{ac}} = \frac{24 \cdot 0.629 \cdot 50 \cdot 10^{-6}}{0.5 \cdot 5 \cdot 1.414} = 213.5 \mu\text{H}$$

The value of intermediate energy transfer capacitor C1 is calculated as

$$C1 = \frac{TP}{2\{\Delta(V_{dc} + V_{ac})\}(V_{dc} + V_{ac})}$$

$$= \frac{50 \cdot 10^{-6} \cdot 50}{2\{0.3(24 + 14 \cdot 1.414)\}(24 + 14 \cdot 1.414)} = 2.17 \mu\text{F}$$

The value of output capacitor C2 is derived as

$$C2 = \frac{I_{dc}}{2\omega\Delta V_{dc}}$$

$$= \frac{2.083}{2 \cdot 2 \cdot \pi \cdot 20 \cdot 10^3 \cdot 0.3 \cdot 24} = 1.15 \mu\text{F}$$

The input filter design is very important for maintaining low harmonic distortion at the input ac mains [7]. The maximum filter capacitance is expressed as

$$Cd = \frac{I_{dc} \tan \theta}{2\pi f_s V_{dc}} = \frac{2.083 \cdot \tan 1}{2 \cdot \pi \cdot 20 \cdot 10^3 \cdot 24} = 49.6 \text{nF}$$

The filter inductor to maintain low ripple is calculated as

$$Ld = \frac{1}{4\pi^2 f_s^2 Cd} = \frac{1}{4 \cdot \pi^2 \cdot (20 \cdot 10^3)^2 \cdot 49.6 \cdot 10^{-9}} = 1.27 \text{mH}$$

V. CONTROL OF PROPOSED SYSTEM

Two control circuits are implemented in the proposed system. Electronic commutation circuit produces PWM signals to trigger the zeta converter switch Sz. A reference voltage is compared to the actual voltage at the output of the zeta converter. The difference is

then modulated using a PID controller and feed to the PWM generator which produces necessary commutation signals for Sz. Another commutation circuit is used to control the switching of the VSI. Conventionally a rotor position sensor is used as a feedback to the commutation circuit to determine the position and commute switches of the VSI appropriately as shown in Table 2. In the proposed system we use back EMF method to determine the position thus eliminating sensors. Back EMF is proportional to magnetic flux times speed and position is a function of magnetic flux. This method consists of comparing the back EMF of different phase and detecting zero crossing points. Once the zero crossing points are detected appropriate switches are triggered after a delay. When the speed varies, the winding characteristics may fluctuate, resulting in variation of back EMF. In such a situation, the DSP has complete control over the determination of zero crossing point. Also, digital filters are implemented to filter out the high frequency switching noise components from the back EMF signal. The commutation algorithm used is the standard BLDC control algorithm. The commutation occurs 30 electrical degrees after the back EMF zero crossing. Due to easy programmability of the microcontroller, the system has much flexibility to operate the motor.

TABLE II
SWITCHING STATES FOR COMMUTATION OF THE BLDC MOTOR

Rotor Position θ	Switching States					
	S_1	S_2	S_3	S_4	S_5	S_6
0 - 60	1	0	0	1	0	0
60 - 120	1	0	0	0	0	1
120 - 180	0	0	1	0	0	1
180 - 240	0	1	1	0	0	0
240 - 300	0	1	0	0	1	0
300 - 360	0	0	0	1	1	0

VI.SIMULATION AND HARDWARE OF PROPOSED SYSTEM

Fig. 3 Simulink model of the proposed BLDC motor drive system

The proposed system is simulated in MATLAB Simulink and is shown in Fig. 3. From Left there is wind power system comprised of Permanent Magnet Synchronous Generator (PMSG) driven by a wind turbine model connected through a 2-mass driven train as shown in Fig. 4 is the supply source to the drive.

Fig. 5 Simulink model of the zeta converter

Fig. 6 Simulink model of the VSI

The VSI implementing back EMF control method is shown in Fig. 6. The dc supply is then converted to ac and fed to the BLDC motor.

Fig. 7 Ac output of the Simulink wind power system

Fig. 7 shows the output of the wind power system for changing wind speeds. The simulation was done for 14m/s to 7 m/s and we can see the change in voltage of the wind turbine.

Fig. 8 dc output of the Simulink zeta converter

The ac supply shown in Fig. 7 is fed to zeta converter through a DBR which is then boosted to around 24V as shown in Fig. 8, where we can observe that change in wind speed is well regulated by the zeta converter to produce steady output.

Fig. 9 Stator currents of BLDC motor

Fig. 10 Back EMF of BLDC motor

Fig. 11 Speed and Torque of BLDC motor

Fig 9,10 and 11 shows the stator current, back emf, speed and torque obtained from the BLDC. Fig 12 shows the power factor obtained for the designed system. We can observe that a near unity power factor is obtained using this system.

Fig. 12 Power factor of the supply

Fig. 13 Hardware setup of the proposed system

The proposed system is implemented in hardware as shown in fig. 13. From top right, 12V ac supply, which is based through a DBR and then fed to the zeta converter. Control circuits of zeta converter and VSI uses PIC16F877A micro-controller. Mosfet P55N is used as switch in zeta converter and VSI. Optocoupler TL250 is used to provide necessary isolation for VSI and zeta converter. A three phase BLDC motor of Telco make 24V, 70W motor is used in the hardware setup. The output dc link voltage has been controlled and correspondingly speed change has been observed. The PF remains nearby unity and the power quality of the proposed PFC drive is improved.

VII. CONCLUSIONS

The wind powered BLDC motor drive using zeta converter with PFC has been proposed and its suitability has been demonstrated using MATLAB simulation and hardware implementation. The proposed system has been designed and modeled appropriately to accomplish the desired objectives. The results have shown that changing wind speed is well modulated by the zeta converter to produce steady output voltage. The speed of BLDC motor has been found proportional to the DC link voltage, so by varying the dc link voltage different speed can be achieved hence a smooth speed control is obtained. Near unity power factor has been observed, hence improved power quality is achieved.

REFERENCES

- [1] B. Singh and R. Kumar, "BLDC Motor-Driven Solar PV Array-Fed Water Pumping System Employing Zeta Converter" IEEE Trans. Ind. App., vol. 52, no. 3, pp. 2315–2322, Jun. 2016.
- [2] A. H. El Khateb, N. Abd. Rahim, J. Selvaraj, and B. W. Williams, "dc-to-dc converter with low input current ripple for maximum photovoltaic power extraction," IEEE Trans. Ind. Electron., vol. 62, no. 4, pp. 2246–2256, Apr. 2015
- [3] R. Kumar and B. Singh, "Buck–boost converter fed BLDC motor drive for solar PV array-based water pumping," in Proc. IEEE Int. Conf. Power Electron. Drives Energy Syst. (PEDES), Dec. 16–19, 2014, pp. 1–6.
- [4] D. D. C. Lu and Q. N. Nguyen, "A photovoltaic panel emulator using a buck–boost dc/dc converter and a low cost micro-controller," Solar Energy, vol. 86, no. 5, pp. 1477–1484, May 2012
- [5] P. Damodharan and Krishna Vasudevan "Sensorless Brushless DC Motor Drive Based on the Zero-Crossing Detection of Back Electromotive Force (EMF) from the Line Voltage Difference," IEEE Trans. Power Electron. , vol. 25, no. 3, pp. 661–668, Sep. 2010.
- [6] A. Singh, B.P. Singh and S. Dwivedi, "AC-DC Zeta converter for power quality improvement in direct torque controlled PMSM drive," Journal of Power Electron., vol. 6, no. 2, pp.146-162, Apr.2006.
- [7] V. Vlatkovic, D. Borojevic, and F. C. Lee, "Input filter design for power factor correction circuits," IEEE Trans. Power Electron. , vol. 11, no. 1, pp. 199–205, Jan. 2005.
- [8] T.-H. Kim and M. Ehsani, "Sensorless control of BLDC motors from near-zero to high speeds," IEEE Trans. Power Electron., vol. 19, no. 6, pp. 1635–1645, Nov. 2004.
- [9] B. Singh, B. N. Singh, A. Chandra, K. Al-Haddad, A. Pandey, and D. P. Kothari, "A review of single-phase improved power quality ac–dc converters," IEEE Trans. Ind. Electron., vol. 50, no. 5, pp. 962–981, Oct. 2003.
- [10] D.C. Martins, "Zeta Converter Operating in Continuous Conduction Mode Using the Unity Power Factor Technique", in Proceedings of IEE PEVSD'96, 1996, pp.7-11.
- [11] Peres, D.C. Martins, and I. Barbi "Zeta converter applied in power factor correction," in Proc. IEEE-PESC'94, 1994, pp. 1152-1157.
- [12] T. Kenjo and S. Nagamori, Permanent Magnet Brushless DC Motors. Oxford, U.K.: Clarendon, 1985.

10.22214/IJRASET

45.98

IMPACT FACTOR:
7.129

IMPACT FACTOR:
7.429

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 (24*7 Support on Whatsapp)