iJRASET

International Journal For Research in
Applied Science and Engineering Technology

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 7 Issue: IV Month of publication: April 2019

DOI: <https://doi.org/10.22214/ijraset.2019.4586>

www.ijraset.com

Call: 08813907089

E-mail ID: ijraset@gmail.com

3481

II. EXISTING DESIGN

A. SEC-DAEC Codes

Linear codes (n, k) has a data articulation of k bits and code articulation of n bits, including $n-k$ balance bits using a reasonable computation. These codes can be addressed by their correspondence check arrange H (with n columns and $n-k$ rows).

Fig. 1 shows the parity-check matrix of a $(22,16)$ bits linear code. The underlying 16 bits identify with the data bits, and the other 6 bits contrast with the correspondence check bits. The syndrome identical to the length of number of correspondence bits in the code. If the syndrome is every one of the zeros, the got word looks at to a code word, and error is present. Something different, an error occurred. For instance, looking at the matrix from Fig. 1, a confusion of 100011 matches the second portion (set apart with a jolt), so a SE is distinguished in that bit and will be modified by turning around its regard. The error is amended by changing the contrasting piece positions.

When a matrix of 001111 is resolved, a DAE is balanced in the first and second bits as that syndrome is the XOR of the first and second columns of the matrix (101100 XOR 100011). As such, we can say that disarranges 100011 (the second area of the cross section), 001111 (XOR of the first and second portions), and 101000 (XOR of the second and third fragments) show that an error occurred in the second bit of the code word, and it must be amended. If the syndrome matches one of the equity bit positions or the XOR of two neighbouring parity columns, by then we can express that no error occurred in the data bits even with a nonzero syndrome.

Fig 2: SEC-DAEC correction for the second bit in the $(22,16)$ code.

The conventional circuit is showed up in Fig. 2, using the second bit of the model ($d1$). The syndrome bits ($s0$ to $s5$) are differentiated and the models that recognize a error in this second piece. The first and third comparators check against the DAE structures, while the second one evaluates the SE pattern. An OR gate perceives whether the comparators recognized an error. A XOR door reviews the error in the second piece ($d1$) if needed.

B. Basis Structure of FPGAs

FPGAs can be acclimated to unequivocal structures and changed when required as a result of their structure subject to reprogrammable method of logic blocks. Lookup tables (LUTs) are one of the sections of these method of logic blocks, used to realize the justification components of the structure. The number and characteristics of the LUTs and distinctive parts depend upon the maker and the thing family.

FPGAs combine six-input LUTs that can complete a six-input limit or two five-input limits if all information sources are shared. A number of estimations have been proposed to diminish an area use in LUT-based FPGAs [9], [10], with some of them [11], keeping an eye on the multi-yield limits given by a part of these FPGAs. Creators are up 'til now coordinating investigation in this point.

III. PROPOSED DESIGN

Two differentiation improvements are discussed: per-bit joined-pattern and multi bit joined-pattern correction.

A. Per-Bit Joined-Pattern Correction with Six Parity Bits

The underneath showed up. 1, is a (22, 16) code with $n = 22$, $k = 16$, and 6 uniformity bits. A syndrome identical to the XOR of two neighbouring portions implies that a DAE was recognized in the bits arranged on those column positions. The customary structure showed up in Fig. 2 can be executed into a Xilinx 7-course of action FPGA in a fundamental way, using a six-input LUT for each comparator and another LUT for the OR and XOR gates (using four data sources). To address a single piece, four differing LUTs are used, as showed up in Fig. 2. Thus, a point of confinement of 64 LUTs are required to perceive and address 16 bits, expecting no upgrade when mapping is done.

A singular LUT can be used to yield a "1" value when the bit must be redressed and "0" for the most part by checking all the models for that bit at the same time. Fig. 3 shows the most ideal approach to store up the three comparators and the OR gate of the second piece into a single six-input LUT (the third piece correction is also drawn). Likewise, the XOR gate that reviews the error has only two wellsprings of data, so a single five-input LUT (with two yields) can be used to address two bits in the meantime. Two commitments of this LUT contrast with the bits to be balanced ($d1$ and $d2$), and the others are the yields of the six-input LUTs for those bits. Along these lines, 3 LUTs would be required for every 2 bits, 24 LUTs to address the 16 data bits.

Fig 3: SEC-DAEC (22,16) per-bit joined pattern correction optimization.

B. Per-Bit Joined-Pattern Correction with Seven Parity Bits

The headway is progressively jumbled while using seven equity bits. We will next separate the (39, 32) SEC-DAEC codes, with 32 data bits and 7 correspondence bits.

Fig4: Check matrix for a SEC-DAEC (39, 32) code

The standard use for (39, 32) would be Similar to the arrangement showed up in Fig. 2 for (22, 16), anyway with a fifth commitment to LUT4 contrasting with the additional piece from the syndrome (and changing the related equipment). This derives 4 LUTs are required to address each piece, up to 128 LUTs for the 32 data bits. In the veritable utilization, the fuse will play out specific enhancements, and this number will decrease. The estimation of this bit must be shared by the three instances of that data bit (the SE and the two double error syndromes). In Fig. 4, identifying with the SE structure for the eleventh piece (d10), the fifth piece is 0(0110001). Meanwhile, the DAE patterns for the eleventh piece (XOR of the abutting sections, set apart in Fig. 4) have moreover a "0" in this fifth segment (1101001 and 1010011).

An AND gate is added to check the yield of the first LUT and the typical shared estimation of s4. A NOT gate is required exactly when the ordinary estimation of the syndrome bit (s4 for this circumstance) is 0. Each segment in this structure (Fig. 4) shares something like one piece a motivating force for the three models (set apart in solid). There is a second upgrade that can be associated when a comparable piece is moved to the second LUT for two unmistakable columns. In Fig. 5, columns 11 and 13 place the fourth syndrome bit in the second LUT.

Fig 5: SEC-DAEC (39, 32) per-bit joined-pattern correction optimization for the bits d10 and d12.

Wellsprings of data are the data bits to be balanced (d10 and d12), the confusion bit that is shared by the three instances of the two segments (s4) and the yields of the first comparators. Appropriately, three LUTs are required for every two data bits to play out the cure. Hence, 48 LUTs are adequate to address the 32 data bits.

C. Multibit Joined-Pattern Correction with Six Parity Bits

It is possible to familiarize an extra headway with the six-piece correspondence codes. It relies upon the probability of moving a bit to the second-step LUT, together with the way in which that only four data sources were used in the alteration LUT (LUT3) showed up in Fig. 3. Looking structure showed in Fig. 1, all the three precedents for the second segment (d1) share a "0" in the second piece (001111, 100011, and 101000).

3485

Fig8: SEC-DAEC (72,64) per-bit joined-pattern Correction for the bits d11 and d12.

F. Multi-Bit Joined-Pattern Correction with Eight Parity Bits

In the multi-bit, the triple error correction is done. By this, the 3 bits are corrected for every 8 data bits. The Look up tables (LUTs) are diminished. The layout is shown below Figure.

Fig9: SEC-DAEC (72,64) multi-bit joined pattern Correction for the bits d11, d12, d13.

Fig15: Simulation for (72,64) Multi-bit Correction

Table1: Comparison of SEC-DAEC (22,16), (39,32), (72,64) codes.

PARAMETERS	(22,16) PER-BIT CORRECTION	(39,32) PER-BIT CORRECTION	(72,64) PER-BIT CORRECTION
SLICES	18	18	32
4 I/P LUTs	34	34	58
BONDED IOB	36	34	57
MAX COMBINATI ONAL DELAY	8.109ns	6.209ns	2.102ns
OFFSET DELAY	5.513ns	5.861ns	6.232ns
GATE DELAY	1.218ns	1.218ns	1.603ns
FAN OUT OF LUT	3	3	1
NET DELAY	0.706ns	0.706ns	0.499ns
MAX FREQUENCY	123.3MHZ	161MHZ	476MHZ
POWER CONSUMPTIO N	0.158mw	0.158mw	0.158mw

V. CONCLUSION

In this paper, we have acquainted a method with improve the decoders for SEC-DAEC codes in FPGAs to the extent resource use by misusing the specific characteristics of this sort of codes, and the unprecedented features fused into current FPGAs. The implementation results for three codes, a (22, 16) SEC-DAEC, a (39, 32) SEC-DAEC, and a (72,64) SEC-DAEC exhibits the proposed structures decrease the advantage utilization of the correction circuit while differentiating it and the customary plans. This diminishing can be up to 14% for the (22, 16) code, 13% for the (39, 32) code and 13% for the (72, 64). Future work will address this likelihood and the utilization of different FPGAs to consider the results and improve the headway of codes with progressively broad words.

VI. ACKNOWLEDGMENT

In this paper, the author named Haindavi, who is an PG Scholar and the author named Jayalakshmi, who is an Associate Professor involved here for completing this paper.

REFERENCES

- [1] Xilinx Solutions for Aerospace & Defense Applications, accessed on Apr. 27, 2016. [Online].
- [2] I. Land and J. Elliot, (2009) "Architecting ARINC 664, Part 7 (AFDX) solutions," Xilinx, Inc., San Jose, CA, USA, Appl. Note XAPP1130 (v1.0.1), accessed on Apr. 27, 2016.
- [3] B. Fiethe, H. Michalik, C. Dierker, B. Osterloh, and G. Zhou, "Reconfigurable system-on-chip data processing units for space imaging instruments," in Proc. Design, Autom. Test Eur. Conf., vol. 1. 2007, pp. 1–6.
- [4] C. L. Chen and M. Y. Hsiao, "Error-correcting codes for semiconductor memory applications: A state-of-the-art review," IBM J. Res. Develop., vol. 28, no. 2, pp. 124–134, Mar. 1984.
- [5] S. Lin and D. J. Costello, Jr., Error Control Coding, 2nd ed. Englewood Cliffs, NJ, USA: Prentice-Hall. 2004.
- [6] A. Neale and M. Sachdev, "A new SEC-DED error correction code subclass for adjacent MBU tolerance in embedded memory," IEEE Trans. Device Mater. Rel., vol. 13, no. 1, pp. 223–230, Mar. 2013.
- [7] A. Dutta and N. A. Touba, "Multiple bit upset tolerant memory using a selective cycle avoidance-based SEC-DED-DAEC code," in Proc. 25th IEEE VLSI Test Symp., May 2007, pp. 349–354.
- [8] 7 Series FPGAs Configurable Logic Block. User Guide, Xilinx, Inc., San Jose, CA, USA, Nov. 2014.
- [9] A. H. Farrahi and M. Sarrafzadeh, "Complexity of the lookup-table Minimization problem for FPGA technology mapping," IEEE Trans. Computer-Aided Design Integrated. Circuits Syst., vol. 13, no. 11, pp. 1319–1332, Nov. 1994.
- [10] J. H. Anderson, Q. Wang, and C. Ravishanker, "Raising FPGA logic density through synthesis-inspired architecture," IEEE Trans. Very Large Scale Integrated. (VLSI) Syst., vol. 20, no. 3, pp. 537–550, Mar. 2012.
- [11] A. Mishchenko, A. S. Chatterjee, and R. K. Brayton, "Improvements to technology mapping for LUT-based FPGAs," IEEE Trans. Computer-Aided Design Integrated Circuits Syst., vol. 26, no. 2, pp. 240–253, Feb. 2007.

10.22214/IJRASET

45.98

IMPACT FACTOR:
7.129

IMPACT FACTOR:
7.429

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 (24*7 Support on Whatsapp)