ISBN: 978-1-948012-17-1

Ethics and Information Technology (ETIT)

DOI: <http://doi.org/10.26480/et.02.2020.166.168>

REVIEW ARTICLE

A REVIEW PAPER ON DESIGN FOR MICROSTRIP PATCH ANTENNA

Hangsa Raj Das^{a*}, Rajesh Dey^b, Sumanta Bhattacharya^c^aDepartment of Electronics & Communication Engineering, M. Tech, ECE, Kalyani Govt Engineering College^bDepartment of Electronics and Communication Engineering, Brainware Group of Institutions-SDET, Kolkata-700125, India^cDepartment of Electronics and Communication Engineering, Cambridge Institute of Technology, Ranchi-835103, India

This is an open access article distributed under the Creative Commons Attribution License CC BY 4.0, which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

ARTICLE DETAILS

Article History:

Received 18 February 2021

Accepted 11 March 2021

Available online 15 March 2021

ABSTRACT

Microstrip patch antenna is mostly used in modern communication devices over conventional antennas mainly because of their size. In this review paper a survey is conducted on commonly used techniques and design used in microstrip antenna papers which has been used by authors for designing of an efficient, low profile, small, compatible, affordable microstrip antenna, mainly used to designed reconfigurable, multiband and wideband antennas, after that a initiator patch design is given with dimensions on which technique will be applied for the analysis of different parameter of antenna.

KEYWORDS

microstrip antenna, techniques, wideband, conventional

1. INTRODUCTION

In today world of wireless communication, recent developments in wireless communication industry continue to derive requirement of small, compatible and affordable microstrip patch antennas. A patch antenna is a narrowband, widebeam antenna fabricated by etching the antenna element pattern in metal trace bonded to an insulating dielectric substrate such as a printed circuit board with a continuous metal layer bonded to the opposite side of the substrate which forms a ground plane (Liu, 2014). The EM waves is produced by an antenna which is so called transducer because it transforms electric current in to EM waves and by receiving vice versa (Yang et al., 2018). Radiation of antenna by changing the current inside a conductor wire is the concept of radiations of antenna. By accelerating or decelerating the current in a straight wire, the current will create a flow which makes the antenna radiate, if current will not flow antenna never radiate (Kim et al., 2003). Common microstrip antenna shapes are square, rectangular, circular and elliptical, but any continuous shape is possible. The resulting structure is less rugged but has a wider bandwidth because such antennas have a very low profile, are mechanically rugged and can be shaped to conform to the curving skin of a vehicle (Yang et al., 2008). They are often mounted on the exterior of aircraft and spacecraft or are incorporated into mobile radio communications devices. Microstrip antennas are best choice for wireless devices because of characteristics like low profile, low weight, ease of fabrication and low cost. Since it is common practice to combine several radars into one wireless and use single antenna. Microstrip antenna suffers from disadvantages like they have less bandwidth and gain (Constatine, 2016). For obtaining multiband and wideband characteristics, different techniques have been used like cutting slot in patch, fractal geometry and DGS (Kidre, 2014; Wen et al., 2012). In order to increase bandwidth DGS has been used. DGS may be realized by cutting shape from ground plane. Shape can be simple or complex. When DGS has been applied to antenna equivalent inductive part due to DGS increases and this cause high effective dielectric constant hence bandwidth reduced. It is to be noted that within particular area of ground different DGS can produce different resonant frequencies and different bandwidth. In this paper two radiating u slot in ground plane have been cut out. Hence new

resonances along with effective current paths are generated in ground plane, as result wideband characteristics have been obtained (Mooszadeh, 2014).

2. LITERATURE SURVEY

A group researcher proposed approach to enhance isolation in microstrip patch antenna arrays is described (Gulam and Malathi, 2014). A Defect is introduced called as meander line resonator by creating defect known as band notch function. Resonator is designed to block surface current at resonant frequency of two patch antenna. This antenna provided an improvement in isolation by 16 dB with reduced edge to edge spacing of 7 mm. This design and simulation have been carried out using antenna simulation software. The resonator is designed to block the surface current at the resonant frequency of the two patch antennas coupled along H- plane and operating at a frequency of 4.8 GHz. The interelement isolation before and after the implementation of SMLR has been investigated.

A group researcher proposed dual beam microstrip antenna, Two radiation beams were obtained by operating patch at higher order mode instead of fundamental mode (Kidre, 2014). In this, bandwidth of antenna is obtained by making use of u shaped patch. Conventional U slot patch antenna, parametric analysis is analyzed. Also effect of U slot inclusion on performance of patch antenna was analyzed. Antenna was designed and simulated using HFSS simulated software and good effects were obtained between practical and experimental results. The antenna operating frequency range is 5.18– 5.8 GHz with VSWR less than 2, which corresponds to 11.8% impedance bandwidth. It exhibits two radiation beams, directed at 35 and with 7.92 dBi and 5.94 dBi realized gain, respectively at 5.5 GHz

A group researcher proposed circular symmetric slotted microstrip patch antenna with compact size (Nasimuddin, 2014). This antenna was obtained by cutting shapes in diagonal directions of microstrip patch antenna. A measured 3 dB axial-ratio (AR) bandwidth of around 0.7% (6.0 MHz) with 2.0% (18.0 MHz) impedance bandwidth was achieved. The

Quick Response Code	This paper was presented at	Access this article online	
	International Conference on Contemporary Issues in Computing (ICIC-2020) - Virtual IETE Sector V, Salt Lake, Kolkata From 25th-26th July 2020	Website: www.intelcomp-design.com	DOI: 10.26480/et.02.2020.166.168

measured boresight gain was more than 3.3 dBi over the operating band was obtained. Different shapes for the slots are studied and compared, based on the fixed overall volume of the antenna for circularly polarized diagonally symmetric slotted microstrip-patch antennas. This antenna was designed to have compact size of small dimensions.

Some researchers proposed triband bowtie antenna using slot technique (Liu, 2014). This antenna was obtained by inserting two pairs of slots with different length of isosceles triangle without increasing area of triangle. This antenna is designed to operate for three different bands applications. Antenna was resonated at three different bands but its dimensions were made for middle frequency band. This antenna was resonated for 3.5 GHz, 4.5 GHz and 5.8 GHz. Design and simulation were carried out using antenna simulation software.

A group proposed small and compact triple band microstrip fed printed monopole antenna for wireless local area network (Moosazadeh, 2014). This antenna was used for Wireless Local area network applications and Wi-Max application. The proposed antenna consists of a rectangular radiating patch with L- and U-shaped slots and ground plane. A parametric study on the lengths of the U- and L-shaped slots of the proposed antenna was provided to obtain the required operational frequency bands—namely, WLAN(2.4/5.2/5.8 GHz) and WiMAX (2.5/3.5/5.5 GHz). The proposed antenna was small (15 15 1.6 mm) when compared to previously well-known double- and triple-band monopole antennas.

3. DESIGN OF THE ANTENNA ELEMENT

The three essential parameters for the design of a rectangular Microstrip Patch Antenna:

- Frequency of operation (f_0): The resonant frequency of the antenna must be selected appropriately. The Mobile Communication Systems uses the frequency range from 2GHz to 6GHz. Hence the antenna designed must be able to operate in this frequency range. The resonant frequency selected for my design is 2.4 GHz.
- Dielectric constant of the substrate (ϵ_r): The dielectric material selected for our design is RT Duroid which has a dielectric constant of 4.4. A substrate with a high dielectric constant has been selected since it reduces the dimensions of the antenna.
- Height of dielectric substrate (h): For the microstrip patch antenna to be used in cellular phones, it is essential that the antenna is not bulky. Hence, the height of the dielectric substrate is selected as 1.6mm.

Hence, the essential parameters for the design are:

- $f_0 = 2.4$ GHz
- $\epsilon_r = 4.4$
- $h = 1.6$ mm

Step 1: Calculation of the Width (W):

The width of the Microstrip patch antenna is given as:

$$W = \frac{C}{2f_0\sqrt{\frac{\epsilon_r + 1}{2}}}$$

Step 2: Calculation of Effective Length (L_{eff}):

The Effective length is :

$$L_{eff} = \frac{C}{2f_0\sqrt{\epsilon_{eff}}}$$

Step 3: Calculation of the Actual Length of Patch (L):

$$L = L_{eff} - 2\Delta L$$

4. INITIATOR PATCH DESIGN

Figure 1: Microstrip Patch antenna design (a) Pi shape (b) I shape (c) T shape

5. RESULTS AND DISCUSSION

Figure 2 Shows microstrip patch antenna designs return loss is $S_{11} < -10$ db. The pi shape patch antenna return loss is -18db and gain is 1db. The T shape patch antenna return loss is -10db and gain is -3db and I shape patch antenna return loss is -15db and gain value is -2db.

Figure 2: Microstrip patch antenna Return loss: Pi, T, I

6. CONCLUSION

This paper shows the review and survey of techniques and design for the designing of efficient microstrip patch antenna. By using one of any above-mentioned technique some of the limitations of conventional microstrip characteristics is improved. This review work is done on some characteristics implemented through different techniques. Nevertheless, useful solution is still less and suffer from different problems like complexity of structure, reduced bandwidth, reduction of gain etc. Hence, the author feels that further research and more work is needed in these areas. After searched the gap of research paper, reached at the point where is a design has been discussed in this paper based on ADS. In this design all the techniques will be used for analysis the parameters OF ANTENNA.

REFERENCES

- BaikSeung-hun, P.J., Na, H., 2004. Design of L-probe Microstrip Patch Antenna. IEEE Antenna and Wireless Propagation Letters, 3, Pp. 117-120.
- Chen, W.L., Wang, G.M., Zhang, C.X., 2009. Bandwidth Enhancement of a Microstrip-Line-Fed Printed Wide-Slot Antenna with a Fractal-Shaped Slot. IEEE Transaction on Antennas and Propagation, Vol.59, No.7, Pp. 2134-2137.
- Constatine, B.A., 2016. Antenna Theory and Analysis Design. A john willey& sons, inc.publication.
- Farnaz, M., Javad, N., Changiz, G., 2012 A Novel Dual-Wide Band Monopole-Like Microstrip antenna withcontrollable Frequency Response. IEEE Antenna and Wireless Propagation Letter, 11, 2012.
- Golpour, M., Koohestani, M., 2009. U-shaped microstrip Patch Antenna with parasitic tuning stubs for Ultra-Wide Band Applications. Published in IET Microwave, Antennas & Propagation.
- Gulam, M., Malathi, S., 2014. Implementation of Slotted Meander-Line Resonators for Isolation Enhancement in Microstrip Patch Antenna Arrays, IEEE Transactions on Antennas and Propagation.
- Ismail, M.Y., Inam, M., Zain, A.F.M., Mughal, M.A., 2010. Phase and Bandwidth enhancement of Reconfigurable Reflect Array Antenna with slots Embedded Patch- IEEE Antenna and Wireless Propagation Letter, 7.
- Jung, W.C., 2011. Ha Sangjun Single Beem Steering Antenna With U-Slot-@ crown.
- Kidre, A., 2014. Wide band dual beam U- slot Microstrip antenna. IEEE transaction of Antennas and Wireless Propagation Letters, 61, Pp. 1415-19.
- Kim, S.Y., Kim, M., Sung, J.Y., 2003. Harmonics Reduction with Defected Ground Structure for a Microstrip Patch Antenna. IEEE Antenna and Wireless Propagation Letters, 2, 2003 pp no 111-112
- Liu, H., 2014. Single feed slotted bowtie antenna for triband application. IEEE Antenna and Wireless Propagation Letter, 12, Pp. 1658-61.
- Liu, W.C., Wu, C.M., Dai, Y., 2011. Design of Triple-Frequency Microstrip-Fed Monopole Antenna Using DefectedGround Structure. IEEE Transaction on Antennas and Propagation, 10, Pp. 2457-2463.
- Moosazadeh, 2014. Compact & small planar monopole antenna with

- symmetrical L- &U- shaped slots for WLAN/WiMAX Applications. IEEE Antenna and Wireless Propagation Letter, 13, Pp. 388-391.
- Nagarajan, V., Chita, R., Jothi, 2013. Double L-Slot Microstrip Patch Antenna for WIMAX and WLAN applications– Department of Electronics and Communication Engineering, Adhiparasakhi Engineering College, Chennai, India. Computers and Electrical Engineering, 39 (3).
- Nasimuddin, 2014. Slotted microstrip antennas for circular polarization with compact size IEEE Antenna and Wireless Propagation Letter, 55, Pp. 127-34.
- Wen, L., Aan-guo, W., Xio-tao, C., 2012. Novel Radiation Pattern Reconfigurable Antenna with six beam choices– Science-Direct.com/Journals, Pp. 123-28.
- Yang, S., Kishk, A.A., Lee, F.K., 2008. Frequency Reconfigurable U-slot Microstrip Patch Antenna. IEEE Antennas and Wireless Propagation Letters, 7, Pp. 127-129.