iJRASET

International Journal For Research in
Applied Science and Engineering Technology

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 8 Issue: XII Month of publication: December 2020

DOI: <https://doi.org/10.22214/ijraset.2020.32469>

www.ijraset.com

Call: 08813907089

E-mail ID: ijraset@gmail.com

Single Diode PV Panel Modeling and Study of Characteristics of Equivalent Circuit

Rahul Narang¹, Dr. M. K. Bhaskar², Manish Sharma³, Manish Parihar⁴, Vinay Sharma⁵

^{1, 2, 3, 4}Department of Electrical Engineering, M.B.M. Engineering College, JNV University, Jodhpur

⁵Department of Electrical Engineering, Vyas Institute of Engineering College, RTU University, Jodhpur

Abstract: In this paper single diode PV model is chosen for simulation of solar cell because it is fast and less complex. Here simulation based on different parameter and there effects on PV characteristics and efficiency, these parameters are irradiation, temperature, parasitic resistance, series cells, parallel cells and ideality factor. By varying anyone parameter keeping other parameter to constant, the pre-required data is obtained from solar panel model simulation is done by matlab software.

Keywords: Single Diode Model, Solar Cell, Matlab, Simulation, PV Characteristics

I. INTRODUCTION

Sun delivers huge amount of energy per year that is almost equals to 21 billion tons of energy generated by burning coal. These spectral of radiation consist of UV, 7 spectral of visible light, irradiation this ranges 250nm to 2500nm and radiation is a form of energy which is very dense as in 550nm it contains $1.75\text{W/m}^2/\text{nm}$. There are two ways to harness this energy into usable, first by using blackbody effect which also applied to white car standing in sunlight, in which sunlight is concentrated and form steam to run turbine to generate electricity, second by photovoltaic (PV) effect which convert sunlight directly into electrical energy. [1] Photovoltaic energy is harness by solar cell, solar cell is an semiconductor which absorbs sunlight and generate photocurrents. [2] Solar power is getting popular because it's free of cost, less service cost, abundant but it has some limitations high cost of manufacturing, less efficiency [2] efficiency can be improved by research in this field, in order to improve efficiency deep detailed simulation work is required to get optimum output power [2]. A faster way to get solar cell simulation is with single diode model it gives faster simulation time due to less no. Of equations and consist 5 parameter. Most of the researchers do simulation with single diode pv model, its equivalent circuit in figure 1 shows 5 parameters that are photo generated current (I_{ph}), diode saturation current (I_0), parasitic resistance series (R_s) & parallel (R_p) and ideality factor [3]

A. Modeling of Single Diode PV Cell

There are several mathematical methods available in those analytical method is simple and fast for calculation of characterization of IV and PV curve [4]. The equivalent circuit consist of series and parallel resistance which represent resistive loss in pv cell, an current source in parallel to circuit (I_{ph}) this current is generated by photons or light and an diode in parallel which represent photo diode which can be made up of different kind of semiconductor material in mono or polycrystalline form. [5]

Fig 1 Equivalent Circuit Diagram of Single Diode PV cell

1) Mathematical Expression

$$I = I_{ph} - I_0 \left[\exp \left(\frac{V + IR_s}{aV_T} \right) - 1 \right] - \frac{V + IR_s}{R_p} \quad (1)$$

$$V_T = \frac{N_s k T}{q} \quad (2)$$

$$I_{ph} = \left(\frac{G}{G_n} \right) [I_{pvn} + k_i (T - T_n)] \quad (3)$$

$$I_0 = I_{on} \left(\frac{T_n}{T} \right)^3 \exp \left[\frac{qE_g}{ak} \left(\frac{1}{T_n} - \frac{1}{T} \right) \right] \quad (4)$$

$$I_{on} = \frac{I_{scn}}{\exp(V_{ocn}/aV_{Tn}) - 1} \quad (5)$$

2) Nomenclature

- a) I is total current at output.
- b) N_s is no. of cells connected in series
- c) I_{ph} is photo generated current
- d) N_p is no. Of cells connected in parallel
- e) I_o is reverse saturation current of diode
- f) a is ideality factor of diode D.
- g) R_s & R_p is series and parallel resistance respectively
- h) I_d is diode current in single diode model
- i) G is Irradiance
- j) V_t is thermal voltage

- 3) **Fill Factor and Efficiency:** The fill factor is the ratio of the actual maximum obtainable power to the product of the open circuit voltage and short circuit current. This is a key parameter in evaluating performance. Fill Factor is a measure of the “squareness” of the IV curve. [13] Efficiency shows the performance of the solar cell which is determined by ratio of output power and the maximum input power get from sun.

$$FF = \frac{V_m I_m}{V_{oc} I_{sc}} \quad (6)$$

$$\eta = \frac{V_{oc} I_{sc} FF}{P_{in}} \quad (7)$$

$$\Delta T = T - T_n \quad (8)$$

B. Simulation of Single Diode Model

Simulation is done under matlab software over single diode model and extracting PV curve and efficiency based on output power .[2][4][[8][9] And observation on 7 parameters one by one while keeping other parameter constant to see exact changes in PV characteristics and efficiency. From equation (1,2,3,4,5) which shows that single diode model is fast to calculate parameters , this simulation can is done by computer simulators or math software like matlab , this help to determine M_{pp} for each iteration of all varying parameter. The data of Adani Eternal series is taken are specified in below table

Table I. Specification of PV Model

Properties	Values
pmax of real module	300w
open circuit voltage (voc)	39.53v
short circuit current (isc)	10.01a
temperature coefficient of voc (kv)	-0.31%/°c
temperature coefficient of isc (ki)	0.068%/°c
reference temperature (tn)	25°c/298k

C. Irradiation

Irradiation absorbed by solar cell under blackbody effect, as the irradiation rises the amount of charge rises hence current rises. As seen from the figure below describes as the irradiation increases the power also increases simultaneously where as no changes is seen in voltage [10]. At 200W/m^2 output power is 48W and at 1000W/m^2 output power is 261W which makes the statement true.

Fig 2 P-V Characteristics at Different Irradiation

Fig 3 Efficiency at Different Irradiation

D. Temperature

As the temperature rises the effect on semiconductor clearly can be seen from the output voltage that decreases with increase in temperature where as no effect on current is seen in IV curve due to same irradiation. at 15°C output power is 280W as the temperature rises to 55°C it decreases to 205W [4][10][11] and efficiency also decreased as described in fig 3.

Fig 4 P-V Characteristics at Different Temperature

Fig 5 Efficiency at Different Temperature

E. Series Resistance

This is a parasitic resistance between junction and output terminal, this resistance happens due to impurities caused by manufacturing defects, and high series resistance can be seen in low-grade solar panels, as this resistance becomes high, the voltage becomes lower, where no effect on the horizontal part of the IV curve.[10][12]

Fig 6 P-V Characteristics at Different Rs

Fig 7 Efficiency at Different Rs

F. Shunt resistance

As the shunt resistance rises the output voltage will be get near to P_{max} and fill factor will get reduced, at low resistance as 355Ω the output power is 261.3W and where 755Ω output power is 262.5W as getting higher resistance power becoming constant as described from fig 5[4][7][10][12]

Fig 8 P-V Characteristics at Different R_p

Fig 10 Efficiency at Different R_p

G. No of Series Cells

Series connection add voltage of each cell as similar to battery, as the series cells increases the output power and voltage increases [13] series string of cells is made to make a panel and later those panels can attach into $m \times n$ size of large array for hotels, factory or industry as this statement described from fig 6 series cells increases power as well as efficiency.

Fig 11 P-V Characteristics at Different N_s

Fig 12 Efficiency at Different N_s

Fig 13 P-V Characteristics at Different N_p

Fig 14 Efficiency at Different N_s

H. No. of Parallel Cells

Parallel connection is based on required load, as the no. Of parallel cell rises the amount of current rises and the voltage will be same, parallel connection can be done in many ways like cell to cell or string to string output power will be same. The power rises with no. Of parallel cell and efficiency also rises

I. Ideality Factor

Ideality factor depends on type of semiconductor and amount of impurities in it and recombination in charge region dominates, the main reason in ideality factor increment is that recombination of charge carrier becoming dominant and this causes increment in depletion layer or junction bandwidth, for ideal diode it is 1 as this factor rises the power and efficient decreases [2][5][7][12].

Fig 15 P-V Characteristics at Different Ideality Factor

Fig 16 Efficiency at Different Ideality Factor

J. Programming Algorithm

- 1) Step1 –Mentioning all variable and constant values.
- 2) Step2 –Start for loop iteration for 1 to 5
- 3) Step3 –Calculate V_t , I_o and I_{ph} values.
- 4) Step4 –start for loop iteration for V from 0 to 40
- 5) Step5 –Calculate I and P for each iteration
- 6) Step6 – Determine FF and Eff. For each iteration of step 2
- 7) Step7 –Increment in parameter on which observation is to be done
- 8) Step8 – Return to step 1 for observation of next parameter

II. CONCLUSION

For development of PV system simulation is done based on real module data provided by manufacturer. In this paper Adani eternal series module is used which gives maximum 300W power, and this simulation is based upon single diode model which requires less equation as mentioned in introduction it has 5 parameters to include in this simulation. And this simulation is done under 7 varying parameters irradiation, temperature, parasitic resistance, series - parallel cells and ideality factor which shows there effect on output power and efficiency .In P-V characteristics M_{pp} is determine all varying parameters which is very useful for manufacturer to track out problems related to real module, thus the single diode model can help in fast simulation and can use in modeling of solar cell in the field of PV technology.

REFERENCES

- [1]. Mahmud Wasfi "Solar Energy and Photovoltaic Systems" <https://www.researchgate.net/publication/230651491>.
- [2]. Mamta Suthar, G.K Singh and R.P Saini "Comparison of Mathematical Models of Photo Voltaic (PV) Module and effect of various Parameters on its Performance" 978-1-4673-6150-7/13/\$31.00 ©2013 IEEE.
- [3]. M. Saqib Ali and S.M. Raza Kazmi "An accurate Analysis Approach for the parameterization of the single diode model of PV cell" arXiv:2005.06698v1 [eess.SY] 13 may 2020.
- [4]. M. Azzouzi, D. Popescu and M. Bouchahdane "Modeling of Electrical Characteristics of pv cell considering Single-Diode Model" doi:10.18178/jocet.2016.4.6.323.

- [5]. Youssef Belkassmi, Kamal Gueraoui, Abdessamade Rafiki and L. Emamouni "Modeling and Simulation of photovoltaic module based on one diode model using matlab/Simulink" <https://www.researchgate.net/publication/322870606>.
- [6]. C. Carrero, J. Amador, S. Arnaltes "A single procedure for helping PV designers to select silicon PV modules and evaluate the loss resistances" doi:10.1016/j.renene.2007.01.001.
- [7]. Md Faysal Nayan, S.M. Safayet Ullah "Modelling of Solar Cell Characteristics Considering the Effect of Electrical and Environmental Parameters" 978-1-5090-0169-9/15/\$31.00 ©2015 IEEE.
- [8]. Jing Jun Soon, Kay-Soon Low and Shu Ting Goh "Multi-dimension Diode Photovoltaic (PV) Model for Different PV Cell Technologies" 978-1-4799-2399-1/14/\$31.00 ©2014 IEEE.
- [9]. Mr. A. Sriharibabu, Mr. J. Jithendranath, Mr. Ch. Uma Maheswara Rao, Dr. G.Durgasukumar "A Novel Two Diode Model of Pv Module for MPPT with Neural Compensator" IJCTA Vol.8, No.1, Jan-June 2015, Pp.237-252 © International Sciences Press, India.
- [10]. Nahla Mohamed, Nor Zaihar Yahaya and Balbir Singh Mahinder Singh "Single-diode model and Two-Diode Model of PV Modules: A comparison" <https://www.researchgate.net/publication/261201261>.
- [11]. Tuyen Nguyen-Duc, Huy Nguyen-Duc, Thinh Le-Viet and Hirotaka Takano "Single diode models of PV modules: a comparison of conventional approach and proposal of a novel model" doi:10.20944/preprints202003.0084.v1.
- [12]. Vivek Tamrakar, S.C. Gupta and Yashwant Sawle "Single-Diode PV Cell Modeling and Study of Characteristics of Single and Two Diode Equivalent Circuit" <https://www.researchgate.net/publication/283004040>.
- [13]. Johannes Greulich, Stefan Rein and Markus Glatthaar "Fill factor analysis of solar cells' current-voltage curves" <https://www.researchgate.net/publication/228035452>.

10.22214/IJRASET

45.98

IMPACT FACTOR:
7.129

IMPACT FACTOR:
7.429

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 (24*7 Support on Whatsapp)