ANALYTICAL BEHAVIOUR OF THE FRACTIONAL FOURIER-LAPLACE TRANSFORM

Sharma V. D.

Arts, Commerce and Science College, Kiran Nagar, Amravati (M.S) India

Email: vdsharma@hotmail.co.in

Abstract: The aim of this paper is to present generalization of fractional Fourier-Laplace transform. We introduce the definition of generalized fractional Fourier-Laplace transform and the Different properties of the kernel are discussed. The Analyticity theorem for the Fractional Fourier-Laplace transform (FrFLT) is proved.

Keywords: Fractional Fourier Transform, Fractional Laplace Transform, Generalized Function, Testing Function Space, Signal Processing

Introduction:

Fourier-related transforms are of central importance in diverse application of science, engineering and technology. It is well known that Fourier transform are powerful integral transform and have innumerable application in variety of disciplines not only in engineering side like signal processing [2], optics communication [2] but also in music, economics and geography like subjects.

Laplace transform are widely used for solving differential and integral equations. In Physics and Engineering it is used for analysis of linear time –invariant systems such as electrical circuit, harmonic oscillators, optical devices and mechanical systems. In the theory of integral transform, Mellin transform has presented a direct and systematic technique for resolution of certain types of classical boundary and initial value problems [4].

The fractional Fourier transforms was introduced by Namias as a Fourier transform of fractional order. This was done starting from fractional powers of the eigen values of the Fourier transform and their corresponding eigen functions. The most important aspect of fractional Fourier transforms is its applicability in time varying signals for which the Fourier transforms fails to work.

Fractional Fourier Transform (FrFT) is a generalization of the ordinary Fourier transform (FT). FrFT was first introduced as a way to solve certain classes of ordinary and partial differential equation arising in quantum mechanics. FrFT has established

itself as a powerful tool for the analysis of time varying signals, especially in optics. FrFT has found applications in areas of signal processing such as repeated filtering, fractional convolution and correlation, beam forming, optimal filter, convolution, filtering and wavelet transform, time frequency representation [12,13]. A comprehensive mathematical frame work on properties and applications of FrFT can be found in [2].

The Linear Canonical transform (LCT) is more general than the fractional Fourier Transform (FrFT). The FrFT has one free parameter α , but the LCT has four parameters to adjust the signal. To present the LCT by another simpler way is to use 2×2 matrix $\begin{bmatrix} a & b \\ c & d \end{bmatrix}$. The Fourier transform and the fractional Fourier transform are the special cases of the Linear Canonical Transform, where $\{a, b, c, d\} = \{0, 1, -1, 0\}$ and $\{\cos \alpha, \sin \alpha, -\sin \alpha, \cos \alpha\}$.

The Fractional Laplace transform plays an important role in many fields, including signal processing, wireless communication etc. The fractional Laplace transform is a special case of complex linear canonical transform [11,14].

Fractional Fourier Transform is defined as

$$FrFT\{f(x)\} = F_{\alpha}(u) = \int_{-\infty}^{\infty} f(x) K_{\alpha}(x, u) dx, \quad ,$$

$$\text{where } K_{\alpha}(x, u) = \sqrt{\frac{1-i \cot \alpha}{2\pi}} e^{\frac{i}{2 \sin \alpha} [(x^2+u^2) \cos \alpha - 2xu]}$$

Generalized Fractional Laplace Transform given by Torre [1] is defined in terms of a kernel is

$$FrLT\{f(t)\} = L_\theta(v) = \int_{-\infty}^{\infty} f(t) K_\theta(t, v) dt$$

where,

$$K_\theta(t, v) = \sqrt{\frac{1-i \cot \theta}{2\pi i}} e^{\frac{t^2}{2} \cot \theta + \frac{v^2}{2} \cot \theta - tv \operatorname{cosec} \theta},$$

θ is not multiple of π

$= \delta(t - u)$, θ is multiple of π

The aim of this paper is to introduce a generalization of Fractional Fourier-Laplace transform (FrFLT). This generalization includes testing function space & distributional generalized fractional Fourier-Laplace Transform (FrFLT) is defined. Some properties of Kernel of FrFLT are obtained. Analyticity theorem for the fractional Fourier-Laplace transform is proved.

Fractional Fourier-Laplace Transform

Conventional Fractional Fourier-Laplace Transform

The fractional Fourier-Laplace transform with parameter α and θ of $f(x, t)$ denoted by $FrFLT\{f(x, t)\}$ performs a linear operation given by the integral transform.

$$FrFLT\{f(x, t)\} = F_{\alpha, \theta}(u, v) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(x, t) K_{\alpha, \theta}(x, u, t, v) dx dt, \quad (2.1)$$

where $K_{\alpha, \theta}(x, u, t, v) =$

$$\sqrt{\frac{1-i \cot \alpha}{2\pi}} \sqrt{\frac{1-i \cot \theta}{2\pi i}} e^{\frac{i}{2 \sin \alpha} [(x^2+u^2) \cos \alpha - 2xu]} e^{\frac{1}{2 \sin \theta} [(t^2+v^2) \cos \theta - 2tv]}, \quad (2.2)$$

The Testing Function Space $E(R^n)$

An infinitely differentiable complex valued smooth function ϕ on R^n belongs to $E(R^n)$, if for each compact set $k \subset S_a, I \subset S_b$, where, $S_a = \{x: x \in R^n, |x| \leq a, a > 0\}$ and $S_b = \{t: t \in R^n, |t| \leq b, b > 0\}$, $k, I \in R^n$

$$\gamma_{E, l, q}(\phi) = \sup_{x \in k} \sup_{t \in I} |D_x^l D_t^q \phi(x, t)| < \infty,$$

$$l, q = 0, 1, 2, \dots$$

Thus $E(R^n)$ will denote the space of all $\phi \in E(R^n)$ with support contained in $S_a \cap S_b$. Moreover, we say that f is a fractional Fourier-Laplace transformable, if it is a member of E^* , the dual space of E .

Generalized Fractional Fourier-Laplace Transform

The distributional fractional Fourier-Laplace transform of $f(x, t) \in E(R^n)$ defined by

$$FrFLT\{f(x, t)\} = F_{\alpha, \theta}(u, v) = \langle f(x, t),$$

$$K_{\alpha, \theta}(x, u, t, v) \rangle,$$

$$\dots\dots\dots(3.1)$$

where $K_{\alpha, \theta}(x, u, t, v) =$

$$\sqrt{\frac{1-i \cot \alpha}{2\pi}} \sqrt{\frac{1-i \cot \theta}{2\pi i}} e^{\frac{i}{2 \sin \alpha} [(x^2+u^2) \cos \alpha - 2xu]} e^{\frac{1}{2 \sin \theta} [(t^2+v^2) \cos \theta - 2tv]}$$

The R.H.S. of equation (3.1) is meaningful

because $K_{\alpha, \theta}(x, u, t, v) \in E$ and $f(x, t) \in E^*$.

Proposition

Generalized fractional Fourier-Laplace transform reduces to conventional Fourier-Laplace transform if

$$\alpha = \frac{\pi}{2}, \theta = \frac{\pi}{2}.$$

Proof: The generalized fractional Fourier-Laplace transform is given as

$$\begin{aligned} FrFLT\{f(t, x)\} &= \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(t, x) K_{\alpha, \theta}(x, u, t, v) dx dt \\ &= \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(x, t) \sqrt{\frac{1-i \cot \alpha}{2\pi}} \sqrt{\frac{1-i \cot \theta}{2\pi i}} e^{\frac{i}{2 \sin \alpha} [(x^2+u^2) \cos \alpha - 2xu]} e^{\frac{1}{2 \sin \theta} [(t^2+v^2) \cos \theta - 2tv]} dx dt \end{aligned}$$

$$\text{Putting } \alpha = \frac{\pi}{2}, \theta = \frac{\pi}{2}$$

$$\begin{aligned} &= \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(t, x) \sqrt{\frac{1}{2\pi}} \sqrt{\frac{1}{2\pi i}} e^{i[-2xu]} e^{\frac{1}{2}[-2tv]} dx dt \\ &= \sqrt{\frac{1}{2\pi}} \sqrt{\frac{1}{2\pi i}} \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(t, x) e^{-ixu} e^{-tv} dx dt \end{aligned}$$

$$FrFLT\{f(t, x)\} = FL(u, v),$$

where $FL(u, v)$ is Fourier-Laplace transform

Properties of kernel of Fractional Fourier-Laplace Transform

To prove : $K_{-\alpha, -\theta}(x, u, t, v) = K_{\alpha, \theta}^*(x, u, t, v)$,

where $*$ denotes the conjugation.

Proof- Consider,

$$\begin{aligned} K_{-\alpha, -\theta}(x, u, t, v) &= \sqrt{\frac{1-icot(-\alpha)}{2\pi}} \sqrt{\frac{1-icot(-\theta)}{2\pi i}} e^{\frac{i}{2 \sin(-\alpha)} [(x^2+u^2) \cos(-\alpha) - 2xu]} e^{\frac{1}{2 \sin(-\theta)} [(t^2+v^2) \cos(-\theta) - 2tv]} \\ &= \sqrt{\frac{1+icot\alpha}{2\pi}} \sqrt{\frac{1+icot\theta}{2\pi i}} e^{\frac{-i}{2 \sin \alpha} [(x^2+u^2) \cos \alpha - 2xu]} e^{\frac{-1}{2 \sin \theta} [(t^2+v^2) \cos \theta - 2tv]} \\ &= K_{\alpha, \theta}^*(x, u, t, v) \end{aligned}$$

In the similar way the following results can be proved, \.

5.2 Result: $K_{\alpha, \theta}(x, u, t, v) = K_{\alpha, \theta}(u, x, v, t)$

5.3 Result : $K_{\alpha, \theta}(-x, u, -t, v) = K_{\alpha, \theta}(x, -u, t, -v)$

5.4 Result:

$$\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} K_{\alpha, \theta}(x, u, t, v) K_{\beta, \gamma}(u, z, v, w) dudv = K_{\alpha+\beta, \theta+\gamma}(x, z, t, w)$$

5.5 To prove

$$\begin{aligned} \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} K_{\alpha, \theta}(x, u, t, v) K_{\alpha, \theta}^*(x, u', t, v') dx dt \\ = \delta(u - u', v - v') \end{aligned}$$

Proof-

$$\begin{aligned}
& \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} K_{\alpha,\theta}(x, u, t, v) K_{\alpha,\theta}^*(x, u', t, v') dx dt \\
&= \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} K_{\alpha,\theta}(x, u, t, v) K_{-\alpha,-\theta}(x, u', t, v') dx dt \\
&= K_0(u, u', v, v') \\
&= \delta(u - u', v - v')
\end{aligned}$$

ANALYTICITY THEOREM

Statement- let $f(x, t) \in E^*(R^n)$ and let its fractional Fourier-Laplace transform be defined as $2DFRMT\{f(x, u, t, v)\} = F_{\alpha,\theta}(u, v) = \langle f(x, t), K_{\alpha,\theta}(x, u, t, v) \rangle$ then $FL^{\alpha,\theta}(u, v)$ is analytic on C^n if the $Supp f \subset S_{a,b}$ such that $S_{a,b} = \{x, t: x, t \in R^n, |x| \leq a, |t| \leq b, a > 0, b > 0\}$ Moreover, $FL^{\alpha,\theta}(u, v)$ is differentiable and $D_{u,v}^{l,q}\{FL^{\alpha,\theta}(u, v)\} = \langle f(x, t), D_{u,v}^{l,q}\{K_{\alpha,\theta}(x, u, t, v)\} \rangle$

Proof:- let, $u = (u_1, u_2, \dots, u_i, \dots, u_n) \in C^n$ and $v = (v_1, v_2, \dots, v_i, \dots, v_n) \in C^n$ be arbitrary but fixed point.

We first prove that ,

$$\frac{\partial}{\partial u_i} \{F^{\alpha,\theta}(u, v)\} = \langle f(x, t), \frac{\partial}{\partial u_i} K_{\alpha,\theta}(x, u, t, v) \rangle$$

For fixed $u_i \neq 0$, choose two concentric circles C and C' with centre at u_i with radii r and r_1 respectively such that $0 < r < r_1 < |u_i|$, let Δu_i be a complete increment satisfying $0 < |\Delta u_i| < r$.

Consider,

$$\begin{aligned}
& \frac{F^{\alpha,\theta}(u_i + \Delta u_i, v) - F^{\alpha,\theta}(u_i, v)}{\Delta u_i} \\
& \langle f(x, t), \frac{\partial}{\partial u_i} K_{\alpha,\theta}(x, u, t, v) \rangle = \langle f(x, t), \psi_{\Delta u_i}(x, t) \rangle
\end{aligned}$$

----- (4.1) $\Rightarrow$

$$\begin{aligned}
& \frac{1}{\Delta u_i} \{ \langle f(x, t), K_{\alpha,\theta}(x, u_i + \Delta u_i, t, v) \rangle - \\
& \langle f(x, t), K_{\alpha,\theta}(x, u_i, t, v) \rangle \} - \\
& \langle f(x, t), \frac{\partial}{\partial u_i} \{K_{\alpha,\theta}(x, u, t, v)\} \rangle
\end{aligned}$$

=

$$\begin{aligned}
& \langle f(x, t), \psi_{\Delta u_i}(x, t) \rangle \\
& \Rightarrow \langle f(x, t), \frac{1}{\Delta u_i} \{K_{\alpha,\theta}(x, u_i + \Delta u_i, t, v) \\
& \quad - K_{\alpha,\theta}(x, u_i, t, v)\} \\
& \quad - \frac{\partial}{\partial u_i} K_{\alpha,\theta}(x, u, t, v) \rangle
\end{aligned}$$

=

$$\langle f(x, t), \psi_{\Delta u_i}(x, t) \rangle$$

$$\begin{aligned}
& \text{where, } \psi_{\Delta u_i}(x, t) = \frac{1}{\Delta u_i} \{K_{\alpha,\theta}(x, u_i + \Delta u_i, t, v) - \\
& K_{\alpha,\theta}(x, u_i, t, v)\} - \frac{\partial}{\partial u_i} \{K_{\alpha,\theta}(x, u, t, v)\}
\end{aligned}$$

For any fixed $x, t \in R^n$ and fixed integer

$$l = l_1, l_2, \dots, l_n$$

$$D_x^l \{K_{\alpha,\theta}(x, u, t, v)\}$$

$$= D_x^l \left\{ \sqrt{\frac{1 - i \cot \alpha}{2\pi}} \sqrt{\frac{1 - i \cot \theta}{2\pi i}} e^{\frac{i}{2 \sin \alpha} [(x^2 + u^2) \cos \alpha - 2xu]} e^{\frac{1}{2 \sin \theta} [(t^2 + v^2) \cos \theta - 2tv]} \right\}$$

$$= D_x^l \left\{ \sqrt{\frac{1 - i \cot \alpha}{2\pi}} e^{\frac{i}{2 \sin \alpha} [(x^2 + u^2) \cos \alpha - 2xu]} A(t) \right\}, \text{ where,}$$

$$A(t) = \sqrt{\frac{1 - i \cot \theta}{2\pi i}} e^{\frac{1}{2 \sin \theta} [(t^2 + v^2) \cos \theta - 2tv]}$$

$$= \sqrt{\frac{1 - i \cot \alpha}{2\pi}} \sum_{m=0}^l \frac{l!}{m! (l-2m)!} \left(\frac{i}{2 \sin \alpha}\right)^{l-m} (2)^{l-2m} (x \cos \alpha$$

$$- u)^{l-2m} \cos^m \alpha e^{\frac{i}{2 \sin \alpha} [(x^2 + u^2) \cos \alpha - 2xu]} A(t)$$

$$= \sum_{m=0}^l \frac{l!}{m! (l-2m)!} \left(\frac{i}{2 \sin \alpha}\right)^{l-m} (2)^{l-2m} (x \cos \alpha -$$

$$u)^{l-2m} \cos^m \alpha K_{\alpha,\theta}(x, u, t, v) \quad \text{----}$$

---(4.2)

Since for any fixed $x \in R^n$ and fixed l & $0 < \alpha \leq \frac{\pi}{2}$,

$D_x^l \{K_{\alpha,\theta}(x, u, t, v)\}$ is analytic inside and on C' ,

we have by Cauchy's integral formula,

$$\begin{aligned}
& D_x^l \psi_{\Delta u_i}(x, t) \\
&= \frac{1}{2\pi i} D_x^l \int_{C'} \{K_{\alpha,\theta}(x, \tilde{u}, t, v)\} \left[\frac{1}{\Delta u_i} \left(\frac{1}{z - u_i - \Delta u_i} \right. \right. \\
& \quad \left. \left. - \frac{1}{z - u_i} \right) - \left(\frac{1}{(z - u_i)^2} \right) \right] dz
\end{aligned}$$

where, $\tilde{u} = u_1, u_2, \dots, u_{i-1}, z, u_{i+1}, \dots, u_n$

$$\begin{aligned}
&= \frac{1}{2\pi i} D_x^l \int_{C'} \{K_{\alpha,\theta}(x, \tilde{u}, t, v)\} \left[\left(\frac{1}{(z - u_i - \Delta u_i)(z - u_i)} \right) \right. \\
& \quad \left. - \frac{1}{(z - u_i)^2} \right] dz
\end{aligned}$$

$$\begin{aligned}
&= \frac{\Delta u_i}{2\pi i} \int_{C'} \frac{D_x^l K_{\alpha,\theta}(x, \tilde{u}, t, v)}{(z - u_i - \Delta u_i)(z - u_i)^2} dz \\
&= \frac{\Delta u_i}{2\pi i} \int_{C'} \frac{Q(x, \tilde{u}, t, v)}{(z - u_i - \Delta u_i)(z - u_i)^2} dz
\end{aligned}$$

But for all $z \in C'$ and x is restricted to

compact subset of R^n , $0 < \alpha \leq \frac{\pi}{2}$

$Q(x, \tilde{u}, t, v) = D_x^l K_{\alpha,\theta}(x, \tilde{u}, t, v)$ as in (4.2) is

bounded by a constant L .

Moreover, $|z - u_i - \Delta u_i| > r' - r > 0$ & $|z - u_i| = r'$

Therefore we have

$$\begin{aligned}
|D_x^l \psi_{\Delta u_i}(x, t)| &= \left| \frac{\Delta u_i}{2\pi i} \int_{C'} \frac{Q(x, \tilde{u}, t, v)}{(z - u_i - \Delta u_i)(z - u_i)^2} dz \right| \\
&\leq \frac{|\Delta u_i|}{2\pi} \int_{C_1} \frac{L}{(r' - r)r'^2} |dz| \\
&\leq \frac{|\Delta u_i|}{2\pi} \frac{L}{(r' - r)r'^2} \int_{C_1} |dz|
\end{aligned}$$

$$\begin{aligned} &\leq \frac{|\Delta u_i|}{2\pi} \frac{L}{(r' - r)r'^2} 2\pi r' \\ &\leq \frac{|\Delta u_i|L}{(r' - r)r'} \end{aligned}$$

Similarly,

$$|D_t^q \psi_{\Delta v_i}(x, t)| \leq \frac{|\Delta v_i|M}{(r' - r)r'}$$

where,

$P(x, u, t, \tilde{v}) = D_t^q K_{\alpha, \theta}(x, u, t, \tilde{v})$ is bounded by a constant M.

Thus as $|\Delta u_i| \rightarrow 0$, $D_x^l \psi_{\Delta u_i}(x, t)$ tends to zero uniformly on the compact subset of R^n , therefore it follows that $\psi_{\Delta u_i}(x, t)$ converges in $E(R^n)$ to zero.

Similarly as $|\Delta v_i| \rightarrow 0$, $D_t^q \psi_{\Delta v_i}(x, t)$ tends to zero uniformly on the compact subset of R^n , therefore it follows that $\psi_{\Delta v_i}(x, t)$ converges in $E(R^n)$ to zero.

Since $f(x, t) \in E^*$, we conclude that equation (4.1) also tends to zero. Therefore $FL^{\alpha, \theta}(u, v)$ is differentiable with respect to u_i and v_i . But this is true for all $i = 1, 2, \dots, n$, hence

$FL^{\alpha, \theta}(u, v)$ is analytic on C^n and $D_{u,v}^{l,q}\{FL^{\alpha, \theta}(u, v)\} = \{f(x, t), D_{u,v}^{l,q}\{K_{\alpha, \theta}(x, u, t, v)\}\}$

Hence proved.

Conclusion:

In the present work generalization of fractional Fourier-Laplace transform is presented. The various properties of the kernel of fractional Fourier-Laplace transform are discussed. Analyticity theorem for the fractional Fourier-Laplace transform is proved. The concept of the Fractional Fourier-Laplace transform have been found to be useful in image processing, signal processing.

References:

- A Torre**, "Linear and radical canonical transform of fractional order", Journal of Computational and applied mathematics, 153 (2003), 477-486.
- H.M. Ozaktas, Z. Zalevskys, M.A. Kutay**, "The Fractional Fourier transform with applications in optics and signal and signal processing", Wiley, New York, 2000.
- Khairnar S.M., Pise R.M. and J.N. Salunke**, "Relation of Finite Mellin Integral transform with Laplace and Fourier transform, Contem. Eng. Sci., Vol 4, 269-288, 2011.
- M.C. Anumaka**, "Analysis of Applications of Laplace/ Fourier transformations in electric

Circuit", IJRRAS, 12(2), 333-339, August 2012.

V.D.Sharma, P.D.Dolas, "Inversion Formula for Two Dimensional Generalized Fouier-Mellin transform and its Applications", Int. Jr. of Advanced Scientific and Technical Research, Issue 1 Vol-2, pp 345-350, Dec. 2011.

V.D. Sharma, P. B. Deshmukh, "Inversion Formula for two dimensional Fractional Fourier-Mellin Transform", International Journal of Mathematics & Education, vol-4 No.-1, March 2014.

V.D.Sharma, A.N.Rangari, "Operational Transform Formulae of Fourier-Laplace transform" Int. Jr. pure appl. Sci. Technol., 15 [2] 2013, pp 62-67.

V.D. Sharma, S.A. Khapre, "Application of Generalized Two Dimensional Fractional Cosine Transform" IJEIT, Vol-3, Issue- 4, Oct-2013.

Meisen Pan, Jianjun Jiang, Fen Zhang, Qiusheng Rong, "Medical Image Registration using Fourier-Mellin Transform", Journal of Computational Information Systems 11: 3 (2015) 1141-1148.

Jun Wang^{1,2}, Zhiyong Xu¹, and Jianlin Zhang, "Image Registration with Hyperspectral Data Based on Fourier-Mellin Transform", International Journal of Signal Processing Systems Vol. 1, No. 1 June 2013

Hassan Kamil Jassim, "Local fractional Laplace decomposition method for nonhomogeneous heat equations arising in fractal heat flow with local fractional derivative", Int. J. Adv. Appl. Math. and Mech. 2(4) (2015) 1-7

Rajneesh Kumar, Dr. Anil Ahlawat, "Removal of Image Blurriness using Fractional Fourier Transform", International Journal of Emerging Research in Management & Technology ISSN: 2278-9359 (Volume-4, Issue-6) June 2015.

K. H. Miah, R. H. Herrera, M. van der Baan, and M. D. Sacchi, "Application of Fractional Fourier Transform in Cepstrum Analysis", AAPG Search and Discovery Article #90173 CSPG/CSEG/CWLS GeoConvention 2011, Calgary, Alberta, Canada, May 9-11, 2011

Alireza Ansari, "The Generalized Laplace Transform and Fractional Differential Equations of Distributed Orders", Differential Equations And Control Processes N 3, 2012 Electronic Journal, Reg. N_C77-39410 At 15.04.2010 Issn 1817-2172.